

Installation Instructions

INSTRUCTIONS PERTAINING TO A RISK OF FIRE, OR INJURY TO PERSONS.

IMPORTANT SAFETY INSTRUCTIONS. SAVE THESE INSTRUCTIONS.

(Failure to follow the warnings and instructions on this sheet could result in fire, injury, failure of product, and/or voiding of warranty.)

1. Do not touch luminaire while lamp is on. Turn off/unplug and allow to cool before replacing lamp.
2. Lamp gets HOT quickly! Contact only switch/plug when turning on.
3. Do not touch hot lens, body, cap, or knuckle.
4. Keep lamp away from materials that may burn.
5. Do not touch lamp at any time. Use a soft cloth. Oil from your skin may damage lamp.
6. Do not operate the luminaire with damaged or missing parts.
7. Do not disassemble luminaire beyond cap removal to facilitate lamp and/or accessory installation or replacement.
8. Remove any debris accumulated in the cap periodically.
9. Do not install luminaire within 10 feet of a pool, spa, or fountain.
10. Have fixture installed in accordance with all applicable installation codes and standards by a person familiar with the construction and operation of the fixture and the hazards involved.
11. Consult a qualified electrician to ensure correct branch circuit conductor.
12. Use only cable rated for low voltage. Cable buried more than 6" must be suitable for direct burial. Direct burial cable may be ordered from Vision3 Lighting.

Installation

1. Thread the light fixture (available separately) in to the internal mounting threads of the MO14 Brass Mounting Stake.
2. Pull the light fixture leads through the wiring hole in the side of the MO14 Brass Mounting Stake.
3. Stick the MO14 Brass Stake Mount in to the ground, as shown, at the desired location. Be careful to not cut or nick the supply cable.
Note: If necessary, soak the ground with water before to soften before installation.
4. Run low voltage direct burial lighting cable to the lighting fixture.
5. Connect the light fixture leads to the power supply cable using connectors (not supplied) suitable for this application, per applicable codes. It is recommended that water tight connectors be used. Note: Be sure the power being supplied by the power supply leads matches the rating on the light fixture label.

