

## Installation Instructions

### INSTRUCTIONS PERTAINING TO A RISK OF FIRE, OR INJURY TO PERSONS.

#### IMPORTANT SAFETY INSTRUCTIONS. SAVE THESE INSTRUCTIONS.

(Failure to follow the warnings and instructions on this sheet could result in fire, injury, failure of product, and/or voiding of warranty.)

1. Do not touch luminaire while lamp is on. Turn off/unplug and allow to cool before replacing lamp.
2. Lamp gets HOT quickly! Contact only switch/plug when turning on.
3. Do not touch hot lens, body, cap or knuckle.
4. Keep lamp away from materials that may burn.
5. Do not touch lamp at any time. Use a soft cloth. Oil from your skin may damage lamp.
6. Do not operate the luminaire with damaged or missing parts.
7. Do not disassemble luminaire beyond cap removal to facilitate lamp and/or accessory installation or replacement.
8. Remove any debris accumulated in the cap periodically.
9. Do not install luminaire within 10 feet of a pool, spa, or fountain.
10. Have fixture installed in accordance with all applicable installation codes and standards by a person familiar with the construction and operation of the fixture and the hazards involved.
11. Use only cable rated for low voltage. Cable buried more than 6" must be suitable for direct burial. Direct burial cable may be ordered from Vision3 Lighting.

#### Installation:

1. Thread the MO18 Mount Cap on to the threaded portion of the Luminaire knuckle (Luminaire available separately or by others).
2. Install and tighten a 1/2" conduit lock nut (supplied separately or by others) to secure the Luminaire to the MO18 Mount Cap.
3. Run low voltage direct burial lighting cable (supplied separately or by others) to the spot the Luminaire will be mounted.
4. Pull the low voltage direct burial lighting cable through the hole in the MO18 Spike Mount.
5. Connect the Luminaire leads to the low voltage direct burial lighting cable using connectors suitable for the application, per applicable codes (connectors not included). It is recommended that water tight connectors be used. Note: Be sure the power being supplied matches the rating on the Luminaire label.
6. Place all of the wiring and connections inside of the wiring compartment 'cup' on the MO18 Spike Mount.
7. Slide the MO18 Mount Cap and Luminaire assembly over the top of the wiring compartment cup on the MO18 Spike Mount.
8. Tighten the Set Screw (1 or 3, depending on option ordered) using the hex tool from the supplied tool kit.
9. Stick the MO18 Spike Mount in to the ground, as shown, at the desired location. Be careful to not cut or nick the low voltage direct burial lighting cable. Note: If necessary, soak the ground with water to soften before installation.
10. If additional aiming is required, loosen the set screw(s), rotate the Luminaire and MO18 Mount Cap in the proper direction, and tighten set screw(s).

Note: Luminaire supplied separately or by others.

