

Installation Instructions

INSTRUCTIONS PERTAINING TO A RISK OF FIRE, OR INJURY TO PERSONS.

IMPORTANT SAFETY INSTRUCTIONS. SAVE THESE INSTRUCTIONS.

(Failure to follow the warnings and instructions on this sheet could result in fire, injury, failure of product, and/or voiding of warranty.)

1. Do not touch luminaire while lamp is on. Turn off/unplug and allow to cool before replacing lamp.
2. Lamp gets HOT quickly! Contact only switch/plug when turning on.
3. Do not touch hot lens, body, cap or knuckle.
4. Keep lamp away from materials that may burn.
5. Do not touch lamp at any time. Use a soft cloth. Oil from your skin may damage lamp.
6. Do not operate the luminaire with damaged or missing parts.
7. Do not disassemble luminaire beyond cap removal to facilitate lamp and/or accessory installation or replacement.
8. Remove any debris accumulated in the cap periodically.
9. Do not install luminaire within 10 feet of a pool, spa, or fountain.
10. Have fixture installed in accordance with all applicable installation codes and standards by a person familiar with the construction and operation of the fixture and the hazards involved.
11. Use only cable rated for low voltage. Cable buried more than 6" must be suitable for direct burial. Direct burial cable may be ordered from Vision3 Lighting.

Mount Surface Mount:

Standard Surface Mount:

1. Install Surface Mount to surface using screws sized appropriately for holding the weight of the Luminaire, Mount Cap, and Surface Mount. Note: Use Surface Mount for a template when laying out mount holes.
2. Run low voltage direct burial lighting cable to the Luminaire through the back of the Surface Mount. Tie a knot in the cable for strain relief.

Tree Surface Mount:

1. Using the Surface Mount as a template, mark the position for the Hanger Bolts on the tree.
2. Screw the Hanger Bolts in to the tree. Note: It is recommended that a Hanger Bolt driver be used (not included) which can be ordered from Vision3 Lighting.
3. Install the first set of Nuts on to the Hanger Bolts. Leave Nuts at least 1/4" to 1/2" offset from the tree.
4. Place Surface Mount over Hanger Bolts and install second set of Nuts inside of Surface Mount.
5. Tighten hardware on both ends of Surface Mount to secure the Surface Mount to the Tree. Note: Periodically adjust Nuts and Surface Mount away from tree to allow for tree trunk growth.
6. Run low voltage direct burial lighting cable to the Luminaire through the back of the Surface Mount. Tie a knot in the cable for strain relief.

Mount Fixture:

1. Feed leads from Luminaire through hole in Mount Cap.
2. Thread Luminaire into Mount Cap.
3. Feed Luminaire leads through Lock Nut.
4. Tighten Lock Nut to secure Luminaire to Cap. Note: Use the Lock Nut in conjunction with the Threaded Mount Cap to ensure that the Luminaire is firmly secured.
5. Connect the Luminaire leads to the power supply cable using appropriate connectors (not supplied) suitable for this application, per applicable codes. It is recommended that water tight connectors be used. Note: Be sure rating on the Luminaire label matches the power being supplied by the power supply leads.
6. Place the Mount Cap over the Surface Mount. Rotate the Mount Cap to the desired position and tighten the set screws on the Mount Cap.

